

## **AMENDMENTS TO THE CLAIMS**

1. (Currently Amended) A transmission apparatus in a CDMA (Code Division Multiple Access) mobile communication system for transmitting a modulated radio signal using a plurality of antennas, the transmission apparatus comprising:

a power amplifier for amplifying the radio signal in a transmission period;

a controller for generating a switching control signal in a non-transmission period; and

a switch for switching the amplified radio signal from the power amplifier between a first and a second antenna in response to the switching control signal,

wherein the transmission period and the non-transmission period comprise a sub-frame,

wherein the non-transmission period is a guard period in each sub-frame for separating the sub-frames, ~~and~~

wherein the guard period is located at the end of each sub-frame, and

wherein said switching is performed during said guard period.

2. (Previously Presented) The transmission apparatus as claimed in claim 1, wherein the controller generates the switching control signal in a guard period of the last time slot among the time slots of the frame.

3. (Original) The transmission apparatus as claimed in claim 2, wherein the guard period has a length of 96 chips.

4. (Original) The transmission apparatus as claimed in claim 2, wherein the controller disables the power amplifier at a start point of the guard period and then outputs the switching control signal when an output level of the power amplifier is lowered to a predetermined level.

5. (Currently Amended) A transmission method in a CDMA (Code Division Multiple Access) mobile communication system for transmitting a modulated radio signal using a plurality of antennas, the transmission method comprising the steps of:

amplifying the radio signal in a transmission period;  
generating a switching control signal in a non-transmission period; and  
switching the amplified radio signal between a first and a second antenna in response to the switching control signal,  
wherein the transmission period and the non-transmission period comprise a sub-frame,  
wherein the non-transmission period is a guard period in each sub-frame for separating the sub-frames, and  
wherein the guard period is located at the end of each sub-frame, and  
wherein said switching is performed during said guard period.

6. (Previously Presented) The transmission method as claimed in claim 5, wherein the switching control signal is generated in a guard period of the last time slot among the time slots of the frame.

7. (Original) The transmission method as claimed in claim 6, wherein the guard period has a length of 96 chips.

8. (Currently Amended) A transmission apparatus in a CDMA (Code Division Multiple Access) mobile communication system for transmitting a modulated radio signal using a plurality of antennas, the transmission apparatus comprising:

a power amplifier for amplifying the radio signal in a transmission period;  
a controller for generating a switching control signal in a non-transmission period; and  
a switch for switching the amplified radio signal by the power amplifier between a first and a second antenna in response to the switching control signal,  
wherein the transmission period and the non-transmission period comprise a sub-frame,  
wherein the non-transmission period is a guard period in each sub-frame for separating the sub-frames, and  
wherein the guard period is located at the end of each sub-frame, and  
wherein said switching is performed during said guard period.

9-10. (Cancelled)

11. (Previously Presented) The transmission apparatus as claimed in claim 8, wherein the guard period has a length of 96 chips.

12. (Previously Presented) The transmission apparatus as claimed in claim 8, wherein the guard period is a downlink non-transmission period of the sub-frame.

13. (Cancelled)

14. (Previously Presented) The transmission apparatus as claimed in claim 12, wherein the downlink non-transmission period is 875 $\mu$ sec.

15. (Previously Presented) The transmission apparatus as claimed in claim 8, wherein the guard period is an uplink non-transmission period of the sub-frame.

16. (Cancelled)

17. (Previously Presented) The transmission apparatus as claimed in claim 15, wherein the uplink non-transmission period is 825 $\mu$ sec.

18. (Currently Amended) A transmission method in a CDMA (Code Division Multiple Access) mobile communication system for transmitting a modulated radio signal using a plurality of antennas, the transmission method comprising the steps of:

amplifying the radio signal in a transmission period;

generating a switching control signal in a non-transmission period; and

switching the amplified radio signal between a first and a second antenna in response to the switching control signal,

wherein the transmission period and the non-transmission period comprise a sub-frame,  
wherein the non-transmission period is a guard period in each sub-frame for separating  
the sub-frames, ~~and~~

wherein the guard period is located at the end of each sub-frame, and  
wherein said switching is performed during said guard period.

19-20. (Cancelled)

21. (Previously Presented) The transmission method as claimed in claim 18, wherein the  
guard period has a length of 16 chips.

22. (Previously Presented) The transmission method as claimed in claim 18, wherein the  
guard period is a downlink non-transmission period of the sub-frame.

23. (Cancelled)

24. (Previously Presented) The transmission method as claimed in claim 22, wherein the  
downlink non-transmission period is 875 $\mu$ sec.

25. (Previously Presented) The transmission method as claimed in claim 18, wherein the  
guard period is an uplink non-transmission period of the sub-frame.

26. (Cancelled)

27. (Previously Presented) The transmission method as claimed in claim 25, wherein the  
uplink non-transmission period is 825 $\mu$ sec.

28-37. (Cancelled)

38. (New) A transmission apparatus in a CDMA (Code Division Multiple Access) mobile communication system for transmitting a modulated radio signal using a plurality of antennas, the transmission apparatus comprising:

- an encoder for encoding data;
- an interleaver for interleaving the encoded data;
- a demultiplexer for demultiplexing the interleaved data into I channel data and Q channel data;
- an I channel spreader for spreading the I channel data;
- an I channel scrambler for scrambling the spread I channel data;
- a Q channel spreader for spreading the Q channel data;
- a Q channel scrambler for scrambling the spread Q channel data;
- a time division multiplexer for time multiplexing the spread I channel data with an I channel midamble sequence, and multiplexing the spread Q channel data with a Q channel midamble sequence;
- an I channel finite impulse response filter for pulse shaping the multiplexed I channel data;
- a Q channel finite impulse response filter for pulse shaping the multiplexed Q channel data;
- an I channel multiplier for modulating the pulse shaped I channel data;
- a Q channel multiplier for modulating the pulse shaped Q channel data;
- an adder for adding the modulated I channel data and the modulated Q channel data;
- a power amplifier for amplifying the added I and Q channel data;
- a controller for generating a switching control signal; and
- a switch for switching during a non-transmission period the amplified I and Q channel data between a first and a second antenna in response to the switching control signal.